



10KV-S11/S13/14 Oil Transformer

Knkong Electric Co.,Ltd
No.25 Street,Hanghai Road,Zhengzhou,Henan,China
+86 371 6021 6611
info@knkong.cn
www.knkong.cn www.knkong.cc www.knkong.ru

Our Service:

- 1.quick response in before sales period help you got order.
- 2.excellent service in production time let you know each step we made.
- 3.reliable quality solve you after sale headache.
- 4.long period quality warranty ensure you can buy without hesitate.

Why Choose Us:

1. One-stop supplier globally.
2. More than 10 years professional experiences in electrical appliance industry.
- 3.We offer professional online technology support for perfecting your electrical solution free.
4. Experienced sales service and suggestion.
5. All the products with accessories under strict quality control and final inspection before shipping.
6. We can assure the powerful competitive price and reliable quality products.
7. Most competitive shipping rate from our own shipping forwarder.
8. Whatever big or small order, we can provide you one-to-one service.

10KV-S11 Oil Transformer main technical data

Rated Capacity (KVA)	High voltage (KV)	Tapping Range	Low voltage (KV)	Frequency (Hz)	Connection Symbol	No-load loss (W)	load loss (W)	No-load Current (%)	Noise level (dB)	Short-circuit impedance (%)	Gauge A x B (mm x mm)	Dimensions L*W*H (mm)	Weight (KG)
30	6 6.3 6.6 10 10.5 11	±5% ±2X 2.5%	0.4	50	D. yn11 E. Y, ynO	100	630	2.3	44	4	400	770X545X890	260
50						130	910	2.0	44		400	790X560X920	320
80						180	1310	1.9	48		400	850X635X980	420
100						200	1580	1.8	48		550	865X685X990	470
160						280	2310	1.6	49		550	1120X740X1050	610
200						340	2730	1.5	51		550	1235X825X1080	750
250						400	3200	1.4	51		550	1275X860X1100	850
315						480	3830	1.4	53		550	1300X870X1170	960
400						570	4520	1.3	53		660	1395X960X1190	1160
500						680	5410	1.2	54		660	1530X1080X1230	1340
630						810	6200	1.1	54	4.5	660	1660X1180X1300	1660
800						980	7500	1.0	57		820	1740X1255X1400	2100
1000						1150	10300	1.0	57		820	1780X1320X1490	2400
1250						1360	12000	0.9	59		820	1855X1345X1580	2850
1600						1640	14500	0.8	59		820	1960X1415X1700	3430

10KV-S13/14 Oil Transformer main technical data

Rated Capacity (KVA)	High voltage (KV)	Tapping Range	Low voltage (KV)	Frequency (Hz)	Connection Symbol	No-load loss (W)		load loss (W)		No-load Current (%)	Noise level (dB)	Short-circuit impedance (%)	Gauge A x B (mm x mm)	Dimensions L*W*H (mm)	Weight (KG)
						S13	S14	S13	S14						
30	6	±5% ±2X 2.5%	0.4	50	D, yn11 Y. ynO	80	80	630/600	505/480	1.4	50	4	400X40C	1005X670X960	280
50						100	100	910/870	730/695	1.2	50		400 X 40C	1005X670X990	390
80						130	130	1310/1250	1050/1000	0.97	52		400X40C	1060 X 715X1040	495
100						150	150	1580/1500	1265/1200	0.97	52		550X55C	1075X735X1060	600
125						170	170	1890/1800	1510/1440	0.84	54		550X55C	1110X750X1100	690
160						200	200	2310/2200	1850/1760	0.84	54		550X55C	1140X780X1130	780
200						240	240	2730/2600	2185/2080	0.74	56		550X55C	1210X815X1150	908
250						290	290	3200/305	2560/2440	0.64	56		550X55C	1290X885X1190	1043
315						340	340	3830/3650	3065/2920	0.64	58		550X55C	1300X880X1230	1190
400						410	410	4520/4300	3615/3440	0.54	58		660 X 66C	1410X975X1300	1430
500						480	480	5410/5150	4330/4120	0.54	60		660X66C	1465 X 980X1390	1648
630						570	570	6200	4960	0.54	60		660X66C	1560X1050X1410	2027
800						700	700	7500	6000	0.48	62		820X82C	1700X1160X1480	2500
1000						830	830	10300	8240	0.42	62		820X82C	1790X1280X1520	2700
1250						970	970	12000	9600	0.36	65		820X82C	1890X1360X1600	3280
1600						1170	1170	14500	11600	0.36	69		820X82C	1970X1430X1700	3500

Knkong Electric Co.,Ltd

No.25 Street,Hanghai Road,Zhengzhou,Henan,China

+86 371 6021 6611

info@knkong.cnEnglish:www.knkong.cnEspañol:www.knkong.ccРусский:www.knkong.ru