

7.2kV primary system diagram

switchgear No.:	KYN28A-02	KYN28A-03A	KYN28A-03B				
switchgear model No.:	KYN28A-12	KYN28A-12	KYN28A-12				
switchgear function	incoming cabinet	filter cabinet	RO building cabinet				
switchgear dimension (W*H*D)	800x2240x1610	800x2240x1610	800x2240x1610				
bus Specification TMY-3X(80X8)							
7.2kV main circuit							
	name	spec&Model No.:	QTY	spec&Model No.:	QTY	spec&Model No.:	QTY
main circuit & electric accessory	operation power	DC220V		DC220V		DC220V	
	vcb	HVX24-25-06-E	1	HVX24-25-06-E	1	HVX24-25-06-E	1
	grounding switch			JN15-12	1	JN15-12	1
	CT	LZZBJ9	3	LZZBJ9	3	LZZBJ9	3
	PT						
	lightning arrester	HY5WS-17/50	3	HY5WS-17/50	3	HY5WS-17/50	3
	fuse						
	display device	GQ-6803	1	GQ-6803	1	GQ-6803	1
	electric Energy Meter						
	ammeter	6L2-A	3	6L2-A	3	6L2-A	3
	voltmeter						
	protection	DMP-3286	1	DMP-3286	1	DMP-3286	1
	zero phase sequence CT						
fault indicator	EKL-4.1	1	EKL-4.1	1	EKL-4.1	1	
Remarks							

微(通)用件登记

描 图

描 核

旧底图总号

底图总号

签 字

日 期

			产品型号 Model	KYN28A-12		 Knkong Electric Co., Ltd www.knkong.cn
			所属代号 Om code			
标记 Mark	修改内容 Modification	日期 Date				
设计 Design	标准 Standard					
校对 Proofreading	审定 Validation		图样标记 Pattern marker	重量 Weight	比例 Proportional	
审核 Audit	日期 Date		共 3 页 Total Page	第 2 页 Article Page		