



Smart Bulb



Q | BroadLink International

For more promotions and supports

web: www.ibroadlink.com
e-mail: support@ibroadlink.com

Overview



APP Dimmable

LB1

Lamp Base: E27
Shape: A60
Rated Power: 6.5W
Rated Voltage: AC 220-240V, 50/60Hz
Luminous Flux: 600lm
Size: φ60x112mm



RGB Color
Color Temp.
APP Dimmable

LB26 R1

Lamp Base: E26
Shape: A19
Rated Power: 10W
Rated Voltage: AC 120V, 50/60Hz
Luminous Flux: 800lm
Size: φ60x117mm



Color Temp.
APP Dimmable

LB27 C1

Lamp Base: E27
Shape: A60
Rated Power: 6.5W
Rated Voltage: AC 220-240V, 50/60Hz
Luminous Flux: 600lm
Size: φ60x112mm



RGB Color
Color Temp.
APP Dimmable

LB27 R1

Lamp Base: E27
Shape: A60
Rated Power: 10W
Rated Voltage: AC 220-240V, 50/60Hz
Luminous Flux: 800lm
Size: φ60x117mm

Indications

Status	Indication
Flashes intermitently (repeat flashing 4 times and off)	Device is in AP Setup mode (waiting to be added). This is the default mode for new product.
Flashes quickly (continuously flash 5 times / sec)	Device is in Smart Setup mode (waiting to be added)
Flashes slowly then always on	Device is being set up and added to network

• Reset for AP Setup

When the bulb is in any conditions (except AP Setup mode), quickly switch it off and on for FIVE (5) times (off > on > off > on...) until the bulb flashes intermittently.

• Reset for Smart Setup

When the bulb is in AP Setup mode, quickly switch it off and on for FIVE (5) times (off > on > off > on...) until the bulb flashes quickly.

Troubleshooting

- I can't add the device in APP, I don't know what is the problem?**
Make sure your Wi-Fi network is 2.4GHz and password contains no more than 32 non-special characters. Make sure the device is in either AP Setup mode or Smart Setup mode before proceeding on APP.
- I can't find the device in Alexa and Google Home APP. How can I do?**
Make sure the device can be controlled from external networks (ex. 4G) in BroadLink APP before discovering in Alexa and Google Home.
Make sure you selected the same region as you've done in BroadLink APP during account linking in Alexa and Google Home APP.

Important notices

- For indoor use in dry environment only.
- Use in open luminaire only.
- This device is not designed for use with emergency exits.
- This device may not work with standard (incandescent) dimmers.