



# Smart Bulb



Q | BroadLink International

For more promotions and supports

web: [www.ibroadlink.com](http://www.ibroadlink.com)  
e-mail: [support@ibroadlink.com](mailto:support@ibroadlink.com)

## Overview



### LB1

Lamp Base: E27  
Shape: A60  
Rated Power: 6.5W  
Rated Voltage: AC 220-240V, 50/60Hz  
Luminous Flux: 600lm  
Size: φ60x112mm



### LB26 R1

Lamp Base: E26  
Shape: A19  
Rated Power: 10W  
Rated Voltage: AC 120V, 50/60Hz  
Luminous Flux: 800lm  
Size: φ60x117mm



### LB27 D1

Lamp Base: E27  
Shape: A60  
Rated Power: 10W  
Rated Voltage: AC 220-240V, 50/60Hz  
Luminous Flux: 800lm  
Size: φ60x117mm



### LB27 R1

Lamp Base: E27  
Shape: A60  
Rated Power: 10W  
Rated Voltage: AC 220-240V, 50/60Hz  
Luminous Flux: 800lm  
Size: φ60x117mm

## Indications

Status	Indication
Flashes intermitently (repeat flashing 4 times and off)	Device is in AP (NoAPP) Setup mode (waiting to be added). This is the default mode for new product.
Flashes quickly (continuously flash 5 times / sec)	Device is in Smart Setup mode (waiting to be added)
Flashes slowly then always on	Device is being set up and added to network

### • Reset for AP (NoAPP) Setup

When the bulb is in any conditions (except AP Setup mode), quickly switch it off and on for FIVE (5) times (off > on > off > on...) until the bulb flashes intermittently.

### • Reset for Smart Setup

When the bulb is in AP (NoAPP) Setup mode, quickly switch it off and on for FIVE (5) times (off > on > off > on...) until the bulb flashes quickly.

## Troubleshooting

- I can't add the device in APP, I don't know what is the problem?**  
Make sure your Wi-Fi network is 2.4GHz and password contains no more than 32 non-special characters. Make sure the device is in either AP Setup mode or Smart Setup mode before proceeding on APP.
- With NoAPP setup, do I still need to use BroadLink APP?**  
With our NoAPP technology, the APP is not required during device setup. After the device setup completes, you can just use Alexa or Google Home APP to discover the device and control it in their APPs or using voice commands with their speakers. Alexa and Google Home support all basic features of the device. If you want to experience more advanced functions such as powerful timers and scenes, we recommend you to download "BroadLink" APP and use the same email to sign up an account to try it.
- I can't find the device in Alexa and Google Home APP. How can I do?**  
Make sure the device can be controlled from external networks (ex. 4G) in BroadLink APP before discovering in Alexa and Google Home. Make sure you selected the same region as you've done in BroadLink APP during account linking in Alexa and Google Home APP

## Important notices

- For indoor use in dry environment only.
- Use in open luminaire only.
- This device is not designed for use with emergency exits.
- This device may not work with standard (incandescent) dimmers.